

K2 Harness Pinout

v2.0

Channel Number on mObridge DSP	Type	Colour	Power
5	Sub	Red = +, Black = -	400w RMS 2ohm, 250w RMS 4 ohm
5	Sub x2 (bridged internally)	Red w/ silver = +, Black w/ silver = -	
6	Normal power	Purple = +, Purple w/ silver = -	75w RMS 4ohm
7	Normal power	White = +, White w/ silver = -	75w RMS 4ohm
8	Normal power	Yellow = +, Yellow/ silver = -	75w RMS 4ohm
1	Normal power	Blue = +, Blue w/silver = -	75w RMS 4ohm
2	High power	Green = +, Green w/silver = -	150w RMS 2ohm, 130w @ 4ohm
3	High power	Orange = +, Orange w/silver = -	150w RMS 2ohm, 130w @ 4ohm
4	Normal power	Grey = +, Grey w/ silver = -	75w RMS 4ohm
9	Normal power	Brown = +, Brown w/ silver = -	75w RMS 4ohm
N/A	Remote Trigger OUT	Pink w/ silver	14v
10	Preout	RCA Jack	
N/A	Power +	Red (Thick Guage)	
N/A	Power -	Black (Thick Guage)	
Phase can be swapped in DSP			

